

# Release Notes for Cisco Catalyst IE3x00 and IE3100 Rugged, IE3400 Heavy Duty, and ESS3300 Series Switches, Cisco IOS XE 17.17.x

---

**First Published:** 2025-03-31

## Introduction

This document provides release information for the following Catalyst IE and Cisco ESS switches:

- Cisco Catalyst IE3100 Rugged Series
- Cisco Catalyst IE3x00 Rugged Series
- Cisco Catalyst IE3400 Heavy-Duty Series
- Cisco Embedded Services 3300 Series

Cisco Catalyst IE3x00 Rugged Series Switches feature advanced, full Gigabit Ethernet speed for rich real-time data—and a modular, optimized design. These Cisco rugged switches bring simplicity, flexibility and security to the network edge, and are optimized for size, power, and performance.

From their end-to-end security architecture to delivering centralized automation and scale with Cisco intent-based networking, the Cisco Catalyst IE3x00 family is the perfect solution to your switching needs in almost any use case.

Cisco Embedded Services 3300 Series Switches (ESS3300) revolutionize Cisco's embedded networking portfolio with 1G/10G capabilities. ESS3300 switches are optimized to meet specialized form-factor, ruggedization, port density, and power needs of many applications requiring customization. They complement Cisco's off-the-shelf Industrial Ethernet switching portfolio.

On ESS3300, the small form factor, board configuration options, and optimized power consumption provide Cisco partners and integrators the flexibility to design custom solutions for defense, oil and gas, transportation, mining, and other verticals. The ESS3300 runs the trusted and feature-rich Cisco IOS XE Software, allowing Cisco partners and integrators to offer their customers the familiar Cisco IOS CLI and management experience on their ESS3300 solutions.

## New Features for Cisco IOS XE 17.17.1

Feature Name	License Level	Description	Supported Platforms	Related Document
G.8032 Ethernet Ring Protection	Network Essentials	This feature enables protection switching for Ethernet ring topologies. It utilizes the G.8032 Ethernet Ring Protection (ERP) protocol version 1, as defined in ITU-T G.8032, to safeguard Ethernet traffic in ring topologies, including those with non-Cisco devices.	IE3100	<a href="#">G.8032 Ethernet Ring Protection</a>
Multicast Support Over Port Channel	Network Essentials	From this release, multicast is supported over port channels or EtherChannels. This ensures that multicast traffic is efficiently distributed across multiple physical links within a port channel while maintaining redundancy and preventing duplicate traffic.	IE3400, IE3400H, IE3300	<a href="#">Configuring Basic IP Multicast Routing</a>
4-pair Power over Ethernet (4PPoE)	Network Essentials	From this release, ESS3300 supports 4-pair power over ethernet (4PPoE) and the maximum power supported per port is 90W. The system PoE has been enhanced to 2160W.	ESS3300	<a href="#">Implementation Options</a>


## Important Notes

### IOx Support for IE3300 Switches

To see if the IE-3300-8P2S switch or IE-3300-8T2S switch supports IOx application environment, check the Hardware Version ID on the switch label. The Hardware Version ID is in the upper-right corner of the label, as shown in the following illustration. Support for the feature is available only with Hardware Version ID 06

or later. In the following illustration, the Version ID appears as "V06" at the end of the string inside the red rectangle in the upper-right corner of the label.

**Figure 1: IE3300 Switch Label**



You also can see the Version ID by entering the **show version** command and examining the output, as shown in the following example:

```
IE-3300# show version

Base Ethernet MAC Address       : b0:c5:3c:99:c8:a0
Motherboard Assembly Number    : 73-101289-11
Motherboard Serial Number      : FOC27151WEZ
Model Revision Number          : V06
Motherboard Revision Number    : B
Model Number                   : IE-3300-8T2S
System Serial Number           : FCW2507P4CV
Top Assembly Part Number       : 68-102662-01
Top Assembly Revision Number   : B0
System FPGA version            : 0.89.2
CIP Serial Number              : 0x1999C8A0
SKU Brand Name                 : Cisco
```

IE-3300-8U2X and IE-3300-8T2X switches have supported IOx since the Cisco IOS-XE 17.4.1 release.

### Startup Config is Always Read from Flash

From Cisco IOS XE Release 17.10.1, the startup configuration is always read from flash. The latest configuration is available only in flash when you save the running config, irrespective of the booted media (for example, flash, sdflash, or usbflash) and the boot mode (install or bundle). If a switch cannot find a configuration in flash, it will try to find one in sdflash.



**Note** Also beginning in the Cisco IOS XE Release 17.10.1, you can configure Cisco Catalyst embedded switches to use USB Flash as the primary boot device. See the [Cisco IOS XE Migration Guide for IIoT Switches](#) on [cisco.com](http://cisco.com).

### SMU Installation: Boot in Install Mode

Software Maintenance Upgrade (SMU) installation is no longer supported in bundle mode. Previously, SMU installation was supported in both bundle boot and install mode. Beginning in Cisco IOS XE 17.9.1, SMU supports patching using install mode only.

SMU installation stops if the device is booted up in bundle mode and syslog messages are displayed. You must boot the switch in install mode to support SMU installation.

If the device is booted up in install mode, SMU installation continues to work as before.

### IE3100: Booting Install Image from SD Card

Booting an install image (packages.conf) from SD card is not recommended. After factory reset, to perform a swap drive sync from SD card to internal flash memory, you must manually boot the image available in the emergency partition so that the swap drive auto restore will occur from the emergency image.

For more information about the SD swap drive, see [Configuring SD Swap Drive](#).

### IE3400: Hardware Changes may Require Action

Some hardware components on the Cisco Catalyst IE3400 Rugged Series and Cisco Catalyst IE3400 Heavy Duty Series switches have changed. The changes, which are automatically handled by the IOS XE software, do not affect switch functionality or the ordering process. New units shipped after May 31, 2022 have the hardware change.

However, you may need to upgrade the software, depending on which base switch and expansions module you have, as shown in the following table.



**Note** For detailed information about affected hardware versions, supported software releases, and instructions for different scenarios, see [Field Notices](#) on Cisco.com.

If you have...	Then...
Older versions (shipped before May 31, 2022) of the base switch and expansion module	No action is required.
Newer versions (shipped after May 31, 2022) of the base switch and expansion module	Deploy one of the supported releases of IOS-XE. Refer to <a href="#">Field Notices</a> on Cisco.com for details that are appropriate to your deployment.
Newer version of the base switch with an older version of the expansion module	
Older version of the base switch with a newer version of the expansion module	

### FPGA Profile

FPGA Profile is supported in Cisco IOS XE release 17.8 and later. In a Cisco IOS XE upgrade from an earlier release that does not support FPGA Profile, for example, an upgrade from Cisco IOS XE 17.7.1 to 17.8.1, the default FPGA Profile is installed. Any features controlled by FPGA Profile that are configured in the switch running the earlier release and that are not included in the default profile will be rejected.



**Note** This feature is supported for Cisco Catalyst IE3400 Rugged Series Switches and Cisco Catalyst IE3400 Heavy-Duty Series Switches.

For example, CTS IPv6 is not supported in the default profile, so CTS IPv6 configurations are rejected during bootup after the upgrade. Similarly, after a Cisco IOS XE upgrade where the cts-ipv6 profile is loaded, existing PRP configurations are rejected upon bootup.

To keep the existing profile and feature configurations after an upgrade:

1. After booting the switch, selected the required FPGA Profile as described in "Changing the FPGA Profile", in [System Management Configuration Guide, Cisco Catalyst IE3x00 Rugged, IE3400 Heavy Duty, and ESS3300 Series Switches](#), chapter "Configuring FPGA Profile".

Do not copy running-config to startup-config or write memory.

2. Reload the switch.

The required feature configurations will not be discarded because they are supported by the selected profile.

### PoE Limitation on IE3x00

Even when using power supplies that can provide up to a supported maximum (for example, 170W, 240W, or 480W) for the PoE budget, the PoE budget for the IE3x00 defaults to 125W regardless of the power supplies used. You can configure the power budget to use the maximum.



**Note** Before changing the power budget, the minimum power requirements for the switch need to be considered as well. Please refer to the data sheet for your switch for more details.

The attached power supply powers the IE3x00 switch operation as well as PoE power. When increasing the maximum PoE budget, you must subtract the power draw of the IE3x00 switch from the capacity of the attached power supply. You do so to prevent the IE3x00 switch from overdrawing the capacity of the attached power supply. For example, the IE3400 switch with an expansion module supports a maximum PoE budget of 480W. The IE3400-8P2S with an attached IEM-3400-8P draws 67W. With a 480W capacity power supply, the maximum you should configure the PoE budget is (480W-67W) 413W.

To use the power supply's maximum supported wattage for the PoE budget, configure the power supply max wattage in global configuration mode as follows:

1. Verify the maximum amount that the power supplies support for the PoE budget.
2. Subtract the operating power of the IE3x00 switch according to its datasheet from the maximum capacity of the power supply. This is your max PoE budget.
3. Enter **power inline max** *max-wattage* to increase the PoE budget based on the power supplies used.

*max-wattage* is the maximum available PoE power.

### IE3200 and IE 3300 with 10Mbps or 100Mbps speed in Half-Duplex Mode

CRC errors were observed on the IE3200 and IE3300 platforms when the switch is configured with 10Mbps or 100Mbps speed in half-duplex mode.

As a workaround, configure **no ptp enable** on the half-duplex interface. This improves ingress and egress latencies considerably and ensures that there are no late collisions (and therefore, no CRC errors).

The issue and workaround apply to Cisco IOS XE releases 17.3.5 and later.

### L3 ACL limitation on usage of L4OP in ACLs

Layer 4 Operator (L4OP) in ACLs is limited by the hardware to a maximum of 8 L4OP (range and gt) for UDP and 8 L4OP for TCP, for a total of 16 global L4OP. Keep in mind that the **range** operator consumes 2 L4OP.

The L4OPs include: gt (greater than), lt (less than), neq (not equal), eq (equal), range (inclusive range).



**Note** The eq does not consume L4OPs. For more information see [QoS Configuration Guide](#).

## Cisco Catalyst IE and ESS Switches: Model Numbers

The following table lists the supported hardware models and the default license levels they are delivered with. For information about the available license levels, see section *License Levels*.

Model Number	Default License Level	Description
IE-3100-4P2S-E	Network Essentials	4 x Gigabit Ethernet 10/100/1000 PoE/PoE+ RJ45 ports, 2 x 100/1000 SFP fiber ports
IE-3100-8P2C-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 PoE/PoE+ RJ45 ports, 2 x dual-purpose 1000Base-T RJ45 or 2 100/1000 SFP fiber ports
IE-3100-18T2C-CC-E	Network Essentials	18 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 x dual-purpose 1000Base-T RJ45 or 2 100/1000 SFP fiber ports, conformal coating
IE-3100-4T2S-E	Network Essentials	4 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2x 100/1000 SFP fiber ports
IE-3100-8T2C-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2x dual-purpose 1000Base-T RJ45 or 2 100/1000 SFP fiber ports
IE-3100-8T4S-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 4x 100/1000 SFP fiber ports
IE-3100-18T2C-E	Network Essentials	18 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2x dual-purpose 1000Base-T RJ45 or 2x 100/1000 SFP fiber ports
IE-3105-8T2C-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2x dual-purpose 1000Base-T RJ45 or 2x 100/1000 SFP fiber ports
IE-3105-18T2C-E	Network Essentials	18 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2x dual-purpose 1000Base-T RJ45 or 2x 100/1000 SFP fiber ports

Model Number	Default License Level	Description
ESS-3300-NCP-E	Network Essentials	Main Board without a cooling plate 2 ports of 10 GE fiber, 8 ports of GE copper. 4 of the 8 GE copper ports can also be combo ports. Terminal Power: 16W
ESS-3300-NCP-A	Network Advantage	Main Board without a cooling plate 2 ports of 10 GE fiber, 8 ports of GE copper. 4 of the 8 GE copper ports can also be combo ports. Terminal Power: 16W
ESS-3300-CON-E	Network Essentials	Main Board conduction cooled 2 ports of 10 GE fiber, 8 ports of GE copper. 4 of the 8 GE copper ports can also be combo ports Terminal Power: 16W
ESS-3300-CON-A	Network Advantage	Main Board conduction cooled 2 ports of 10 GE fiber, 8 ports of GE copper. 4 of the 8 GE copper ports can also be combo ports Terminal Power: 16W
ESS-3300-24T-NCP-E	Network Essentials	Main Board with a 16p Expansion Board without a cooling plate 2 ports of 10 GE fiber, 24 ports of GE copper 4 of 8 GE ports can be combo ports on mainboard 4 of 16 GE ports can be combo ports on expansion board Terminal Power: 24W
ESS-3300-24T-NCP-A	Network Advantage	Main Board with a 16p Expansion Board without a cooling plate 2 ports of 10 GE fiber, 24 ports of GE copper 4 of 8 GE ports can be combo ports on mainboard 4 of 16 GE ports can be combo ports on expansion board Terminal Power: 24W

Model Number	Default License Level	Description
ESS-3300-24T-CON-E	Network Essentials	Main Board with a 16p Expansion Board conduction cooled 2 ports of 10 GE fiber, 24 ports of GE copper 4 of 8 GE ports can be combo ports on mainboard 4 of 16 GE ports can be combo ports on expansion board Terminal Power: 24W
ESS-3300-24T-CON-A	Network Advantage	Main Board with a 16p Expansion Board conduction cooled 2 ports of 10 GE fiber, 24 ports of GE copper 4 of 8 GE ports can be combo ports on mainboard 4 of 16 GE ports can be combo ports on expansion board Terminal Power: 24W
IE-3200-8T2S-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE
IE-3200-8P2S-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 PoE/PoE+ ports, 2 fiber 100/1000 SFP-based ports; PoE power budget of 240W
IE-3300-8T2S-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE
IE-3300-8P2S-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 PoE/PoE+ ports, 2 fiber 100/1000 SFP-based ports; PoE power budget of 360W (including expansion module)
IE-3300-8T2S-A	Network Advantage	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE
IE-3300-8P2S-A	Network Advantage	8 x Gigabit Ethernet 10/100/1000 PoE/PoE+ ports, 2 fiber 100/1000 SFP-based ports; PoE power budget of 360W (including expansion module)
IE-3300-8T2X-A	Network Advantage	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 1/10 Gigabit Ethernet SFP-based ports, non-PoE
IE-3300-8T2X-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 1/10 Gigabit Ethernet SFP-based ports, non-PoE
IE-3300-8U2X-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 4PPoE (802.3bt type 3) ports, 2 fiber 1/10 Gigabit Ethernet SFP-based ports; PoE power budget of 480W



Model Number	Default License Level	Description
IE-3300-8U2X-A	Network Advantage	8 x Gigabit Ethernet 10/100/1000 4PPoE (802.3bt type 3) ports, 2 fiber 1/10 Gigabit Ethernet SFP-based ports; PoE power budget of 480W (requires and expansion module to deliver 480W)
IE-3400-8T2S-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE
IE-3400-8T2S-A	Network Advantage	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports, non-PoE
IE-3400-8P2S-E	Network Essentials	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports with PoE
IE-3400-8P2S-A	Network Advantage	8 x Gigabit Ethernet 10/100/1000 RJ45 ports, 2 fiber 100/1000 SFP-based ports with PoE
IE-3400H-8T-E	Network Essentials	8 x 1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-8T-A	Network Advantage	8 x 1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-8FT-E	Network Essentials	8 x 100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .
IE-3400H-8FT-A	Network Advantage	8 x 100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .
IE-3400H-16T-E	Network Essentials	16 x 1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-16T-A	Network Advantage	16 x 1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-16FT-E	Network Essentials	16 x 100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .
IE-3400H-16FT-A	Network Advantage	16 x 100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .

Model Number	Default License Level	Description
IE-3400H-24T-E	Network Essentials	24 x 1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-24T-A	Network Advantage	24 x 1-Gbps X-Coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, mini-change input for Single power source
IE-3400H-24FT-E	Network Essentials	24 x 100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .
IE-3400H-24FT-A	Network Advantage	24 x100-Mbps D-coded ports, 1 Alarm input and 1 Alarm output, 1 Console port, Mini-change input for Single Power Source .

## WebUI System Requirements

The WebUI is a web browser-based switch management tool that runs on the switch. The following subsections list the hardware and software required to access the WebUI.

### Minimum Hardware Requirements

Processor Speed	DRAM	Number of Colors	Resolution
233 MHz minimum <sup>1</sup>	512 MB <sup>2</sup>	256	1280 x 800 or higher

<sup>1</sup> We recommend 1 GHz

<sup>2</sup> We recommend 1 GB DRAM

### Software Requirements

#### Operating Systems

- Windows 10 or later
- Mac OS X 10.9.5 or later

#### Browsers

- Google Chrome: Version 59 or later (On Windows and Mac)
- Microsoft Edge
- Mozilla Firefox: Version 54 or later (On Windows and Mac)
- Safari: Version 10 or later (On Mac)

## Upgrading the Switch Software

This section covers the various aspects of upgrading or downgrading the device software.



**Note** See the [Cisco IOS XE Migration Guide for IIoT Switches](#) for the latest information about upgrading and downgrading switch software.

### Finding the Software Version

The package files for Cisco IOS XE software can be found on the system board's internal flash memory device (flash:) or an external USB, depending on the device configuration.

You can use the **show version** privileged EXEC command to see the software version that is running on your switch.



**Note** Although the **show version** output always shows the software image running on the switch, the model name shown at the end of this display is the factory configuration and does not change if you upgrade the software license.

You can also use the **dir filesystem:** privileged EXEC command to see the names and versions of other software images that you might have stored in flash memory.

### Software Images 17.17.x

The following table provides the file names for the IOS XE 17.17.x software images for Cisco Catalyst IE3x00 Rugged, IE3400 Heavy Duty, ESS3300, and IE3100 Rugged Series Switches.

Release	Image Type	Platform	File Name
Cisco IOS XE.17.17.1	Universal	IE3x00 (IE3200, IE3300, IE3400, and, IE3400H)	ie3x00-universalk9.17.17.01.SPA.bin
		ESS3300	ess3x00-universalk9.17.17.01.SPA.bin
		IE3100 and IE3105	ie31xx-universalk9.17.17.01.SPA.bin

### Automatic Boot Loader Upgrade

When you upgrade from the existing release on your switch to a later or newer release for the first time, the boot loader may be automatically upgraded, based on the hardware version of the switch. If the boot loader is automatically upgraded, it will take effect on the next reload.

For subsequent Cisco IOS XE releases, if there is a new bootloader in that release, it may be automatically upgraded based on the hardware version of the switch when you boot up your switch with the new image for the first time.



**Caution** Do not power cycle your switch during the upgrade.

Scenario	Automatic Boot Loader Response
If you boot Cisco IOS XE the first time	Boot loader may be upgraded to version "8.1.2" for IE3x00 and ESS-3300.  Checking Bootloader upgrade... ... Bootloader upgrade successful

## Software Installation Commands



**Note** For the **install** command to be successful, it is recommended to have a minimum of free space that is twice the size of the image in flash. If there is not enough space available in flash, you are advised to free up space in flash either by issuing the **install remove inactive** command or to manually clean up the flash by removing unwanted core files or any other files that occupy a large amount of space in flash.

Summary of Software Installation Commands for Install Mode	
To install and activate the specified file, and to commit changes to be persistent across reloads— <b>install add file</b> <i>filename</i> [ <b>activate commit</b> ]	
<b>add file tftp:</b> <i>filename</i>	Copies the install file package from a remote location to the device and performs a compatibility check for the platform and image versions.
<b>activate</b> [ <b>auto-abort-timer</b> ]	Activates the file, and reloads the device. The <b>auto-abort-timer</b> keyword automatically rolls back image activation.
<b>commit</b>	Makes changes persistent over reloads.
<b>remove</b>	Deletes all unused and inactive software installation files.

## Licensing

The information about the licensing packages for features available on Cisco Catalyst IE3x00 Rugged, IE3400 Heavy Duty, and ESS3300 Series Switches and Cisco Catalyst IE3100 Rugged Series Switches are available at: <https://www.cisco.com/c/en/us/td/docs/iot/collections/cisco-iiot-licensing.html>.

## Caveats

Caveats describe unexpected behavior in Cisco IOS XE releases. Caveats listed as open in a prior release are carried forward to the next release as either open or resolved.

### Cisco Bug Search Tool

[Cisco Bug Search Tool](#) is a web-based tool that acts as a gateway to the Cisco bug tracking system that maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. BST provides you with detailed defect information about your products and software.

Click the link for the caveat in the sections below to view details for the caveat in Bug Search Tool.

## Open Caveats in Cisco IOS XE 17.17.1

Identifier	Description
<a href="#">CSCwn88892</a>	%IMSP_ACLMGR-3-INVALIDACL: Add access-list failed error on IE3400 switches
<a href="#">CSCwo38334</a>	Web UI log in page loads slow compared to 17.06.05 release

## Resolved Caveats in Cisco IOS XE 17.17.1

Identifier	Description
<a href="#">CSCwj68054</a>	MAT event not working on EEM for IE3400 switches.
<a href="#">CSCwk86434</a>	Configuration failed to parse with a good ciscotr.cfg.
<a href="#">CSCwm30681</a>	Device not able to ping on trunk port when "vlan dot1q tag native" is configured globally..
<a href="#">CSCwm33057</a>	Slowness on IE-3100 when polling snmp OIDs.
<a href="#">CSCwm36038</a>	ESS-3300 forwards unicast traffic to all promiscuous ports.
<a href="#">CSCwm47470</a>	Endpoints with 10 Mbps speed in Half-Duplex Mode drops the connection.
<a href="#">CSCwm48006</a>	C9300 fails to establish proper STP connection with connected device when interface goes down.
<a href="#">CSCwm55828</a>	Websocket connection will not establish using ida.
<a href="#">CSCwm85265</a>	REP ZTP functioning incoherent.
<a href="#">CSCwn62607</a>	IE3100-PN connect issues due to out of AR resources.
<a href="#">CSCwn65142</a>	Disable REP NEG as REP ZTP functioning incoherent.
<a href="#">CSCwo33351</a>	IE3xxx/S5800/S5200: Observed "rep bpduleak" CLI in latest image.

## Troubleshooting

For the most up-to-date, detailed troubleshooting information, see the Cisco TAC website at this URL:

<https://www.cisco.com/en/US/support/index.html>

Go to **Product Support** and select your product from the list or enter the name of your product. Look under Troubleshoot and Alerts, to find information for the problem that you are experiencing.

## Related Documentation

Information about Cisco IOS XE at this URL: <https://www.cisco.com/c/en/us/products/ios-nx-os-software/ios-xe/index.html>

All support documentation for Cisco Catalyst IE3100 Rugged Series Switches is at this URL: <https://www.cisco.com/c/en/us/support/switches/catalyst-ie3100-rugged-series/series.html>

All support documentation for Cisco Catalyst IE3200 Rugged Series Switches is at this URL: <https://www.cisco.com/c/en/us/support/switches/catalyst-ie3200-rugged-series/tsd-products-support-series-home.html>

All support documentation for Cisco Catalyst IE3300 Rugged Series Switches is at this URL: <https://www.cisco.com/c/en/us/support/switches/catalyst-ie3300-rugged-series/tsd-products-support-series-home.html>

All support documentation for Cisco Catalyst IE3400 Rugged Series Switches is at this URL: <https://www.cisco.com/c/en/us/support/switches/catalyst-ie3400-rugged-series/tsd-products-support-series-home.html>

All support documentation for Cisco Catalyst IE3400H Heavy Duty Series Switches is at this URL: <https://www.cisco.com/c/en/us/support/switches/catalyst-ie3400-heavy-duty-series/tsd-products-support-series-home.html>

All support documentation for Cisco ESS3300 Series Switches is at this URL: <https://www.cisco.com/c/en/us/support/switches/embedded-service-3000-series-switches/tsd-products-support-series-home.html>

Cisco Validated Designs documents at this URL: <https://www.cisco.com/go/designzone>

To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: <http://www.cisco.com/go/mibs>

## Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions, and services, visit [Cisco DevNet](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

### Documentation Feedback

To provide feedback about Cisco technical documentation, use the feedback form available in the right pane of every online document.

### **Cisco Support Community**

Cisco Support Community is a forum for you to ask and answer questions, share suggestions, and collaborate with your peers. Join the forum at: <https://supportforums.cisco.com/index.jspa>.

### **Cisco Feature Navigator (CFN)**

The [Cisco Feature Navigator](#) provides links to browse Cisco products and find relevant features and licenses. It also allows you to compare platforms, determine common features between products, and identify unique product features.

The CFN also has a tab that provides a [MIB Locator](#).

---

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2025 Cisco Systems, Inc. All rights reserved.